



RouteSms

BULK HTTP API Specification (LABROC)

(Document Version 1.1)

(This Document gives details on how to send messages via the Bulk HTTP API for the RouteSms Labroc System)



HTTP API to submit messages on SMPP:

http://IP:port/bulksms/sendsms?
 username=XXXX&password=YYYYY&type=Y&dlr=Z&destination=QQQQQQQQQ&source=RRRR&message=SSSSSSS<&url=KKKK>

IP: smpp5.routesms.com

port: 8080 or 8000 (Use port 8000 incase if not able to connect using port 8080)

Parameters are explained below, please note that all the parameters (especially message and url) should be URL-UTF-8 encoded.

username: User name of the SMPP Account

password: Password of the SMPP Account

type: Indicates the type of message.

Values for "**type**":-

- 0: Plain Text (GSM 3.38 Character encoding)
- 1: Flash Message (GSM 3.38 Character encoding)
- 2: Unicode
- 3: Reserved
- 4: WAP Push
- 5: Plain Text (ISO-8859-1 Character encoding)
- 6: Unicode Flash
- 7: Flash Message (ISO-8859-1 Character encoding)

dlr: Indicates whether the client wants delivery report for this message

Range of values for "**dlr**":-

- 0: No Delivery report required
- 1: Delivery report required

destination: Mobile Number to which to Send message to (may or may not include a '+' sign), multiple mobile numbers can be separated by commas (note the comma (',') should be URL encoded).

source: The sender address that should appear in the message

Max Length of 18 if Only Numeric

Max Length of 11 if Alpha numeric

If you wish plus ('+') should be prefixed to the sender address when the message is displayed on the cell phone, please prefix the plus sign to your sender address while submitting the message (note the plus sign should be URL encoded). Additional restrictions on this field may be enforced by the SMSC.

message: The message to send (Can be used for 'long' messages, that is, messages longer than 160 characters for plain text, 140 for flash and 280 for Unicode)

For concatenated (long) messages we will be counting as one message for every 153 characters for plain text and 268 characters for Unicode, as the rest of the characters will be used by the system for packing extra information for re-assembling the message on the cell phone.

In case of WAP Push (type = 4), this is the text that would appear in the message. Also in the latter case, to send non-English characters in the



message, you only have to directly URL encode them (using UTF-8 character encoding scheme).

url: If sending a WAP Push message (type=4), this holds the link that you wish to send, for any other type of message, no value needs to be supplied for this field (if specified will be ignored) . Just like “message” field, this field should also be URL encoded with UTF-8 character encoding (even for sending non-ASCII domain names).

Error Codes:

- 1701:**Success**, Message Submitted Successfully, In this case you will receive the response **1701|<CELL_NO>:<MESSAGE ID>**, The message Id can then be used later to map the delivery reports to this message.
- 1702:Invalid URL Error, This means that **one of the parameters was not provided** or left blank
- 1703:Invalid value in **username** or **password** field
- 1704:Invalid value in "**type**" field
- 1705:Invalid **Message**
- 1706:Invalid **Destination**
- 1707:Invalid **Source** (Sender)
- 1708:Invalid value for "**dlr**" field
- 1709:User validation failed**
- 1710:Internal Error
- 1025:Insufficient Credit**

Note:-

- Along with the above errors codes, standard SMPP v3.4 error codes may also be returned where applicable.
- **Apart from 1709, Please DO NOT RETRY re-sending the message for any other error code (including SMPP v3.4 Error codes) .**
- For better security you can also use the HTTPS protocol for submitting your messages so that your requests are encrypted when being sent over the Internet. To use the HTTPS protocol(when calling this link from a browser) just change the protocol in the link from HTTP to HTTPS and use port “8181” instead of “8080” as illustrated below (note that you might get a security error as RouteSms currently uses a self signed certificate, you will need to add an exception to continue with the message sending process):-
<https://smpp5.routesms.com:8181/bulksms/sendsms?username=XXXX&password=YYYY&type=Y&dlr=Z&destination=QQQQQQQQ&source=RRRR&message=SSSSSSSS>
- While sending messages with type=0 there are some special characters which end up taking the space of more than one character after final encoding and while sending to the SMSC. The following is the list of such known characters:-

Character	Character	GSM 03.38
^	Circumflex Accent	0x1B14
{	Left Curly Bracket	0x1B28
}	Right Curly Bracket	0x1B29

\	Reverse Solidus (Backslash)	0x1B2F
[Left Square Bracket	0x1B3C
~	Tilde	0x1B3D
]	Right Square Bracket	0x1B3E
	Vertical Bar	0x1B40
€	Euro Sign	0x1B65

Please do note that the above list is not exhaustive and hence before sending any special characters do test to see if they are supported.

Notes on WAP Push:-

- WAP Push messages are sent in binary mode and hence only one hundred and forty, eight bit characters (octets) are allowed in a single message, also due to the nature of the message approximately thirty two characters are used to pack the document encoding standards so that the phone recognizes the message correctly. As a result only approximately one hundred and eight characters are available to send in each message (URL + message to display). However if your URL contains some common patterns they are encoded to occupy less space as shown below:-

Pattern	Length	Actual Length
http://	7	1
http://www.	11	1
https://	8	1
https://www.	12	1
.com/ .edu/ .net/ .org/	4	1 [if at the end of the link eg: http://www.routesms.com/] 3 [if in the link, eg: http://www.routesms.com/bulksms]

Apart from the exceptions in the previous table, all other characters are encoded using the UTF-8 character encoding, thus expanding the range of characters supported in a WAP Push (both “message” and “url”). Please refer to the home page of the [Unicode Consortium](http://www.unicode.org) for more details like list of supported characters and how many octets a specified character would consume as per the UTF-8 encoding scheme.

- Long WAP Push messages:** If the total message length after encoding the document encoding standards with the message text and the URL exceed one hundred and forty octets, your account will automatically be charged the excess credits. For WAP Push messages longer than one hundred and forty octets, the number of octets usable for the message text and URL in each message part is further reduced from approximately one hundred and eight to one hundred and three only.

Bulk SMS API Reply Format:

```
<Error_Code>|<destination>:<message_id>,<Error_Code>|
<destination>:<message_id>...
```

Exceptional Situations:-

A request containing multiple destinations will be aborted immediately if any error other than “Invalid Destination” is found, in case an invalid destination is found we just skip that destination and proceed to the next destination.

If while processing the request the SMPP Server goes down, the HTTP API will retry a fixed number (with a gap of ten milliseconds between consecutive retries) of times to reconnect to the SMPP server and submit the message. In case the SMPP server does not come up before the fixed number of attempts are exhausted, the batch will be aborted at that destination and a message will be returned in following format:-

```
<Error_Code>|<destination>:<message_id>,<Error_Code>|
<destination>:<message_id>,1709|<destination_at_which_batch_aborted>
```

The third and final situation which can arise is the the credits can get exhausted in the middle of a request being serviced. In case such a situation occurs we will be aborting the batch on the destination at which we got the “Insufficient_Credit” error, and a response in the following format will be returned to the client:-

```
<Error_Code>|<destination>:<message_id>,<Error_Code>|
<destination>:<message_id>,1025|<destination_at_which_batch_aborted>
```

Example Link to Submit Plain Text Messages (GSM 03.38 character set):

<http://smpp5.routesms.com:8080/bulksms/sendsms?username=XXXX&password=YYYYY&type=0&dlr=1&destination=%2B9198181818&source=routesms&message=Demo%20Message!!!>

The following observations can be made in the above URL:-

1. 'type=0', indicates this is a message of type plain text, this mode supports all characters falling under the GSM 03.38 character set.
2. 'dlr=1', indicates delivery report for this message is enabled.
3. 'message=Demo%20Message!!!', The message field contains the content to send in an URL encoded format, on using the appropriate username and password in the above link you will get the 'Demo Message!!!' on your mobile phone.
4. 'destination=%2B919920315110', An optional plus is included in the destination field here, Do note that the '+' sign is URL encoded.

Example Link to Submit Plain Text Messages (ISO-8859-1 Character set):

<http://smpp5.routesms.com:8080/bulksms/sendsms?username=XXXX&password=YYYYY&type=5&dlr=0&destination=91981818181&source=routesms&message=Demo%20Message!!!>

The following observations can be made in the above URL:-

1. 'type=5', indicates message is of type plain text, this mode supports all characters falling under the ISO-8859-1 character set.
2. 'dlr=0', indicates delivery report for this message is not enabled.
3. 'message=Demo%20Message!!!', the message field contains the message to send in an URL encoded format, on using the appropriate username and

password in the above link you will get the message "Demo Message!!!" on your mobile phone.

4. 'destination=919920315110' , the optional '+' has been omitted.

Example Link to Submit Flash Messages (GSM 03.38 Character set):

<http://smpp5.routesms.com:8080/bulksms/sendsms?username=XXXX&password=YYYYY&type=1&dlr=0&destination=91981818181&source=routesms&message=Demo%20Message!!!>

On calling the above link by replacing the username and password by your account username and password, the message 'Demo Message!!!' should display on your cell phone.

The characters in the message field should fall in the GSM 03.38 character set and the type parameter has to be set to 1 i. e. (type=1).

Example Link to Submit Unicode Flash Messages :

<http://smpp5.routesms.com:8080/bulksms/sendsms?username=XXXX&password=YYYYY&type=6&dlr=0&destination=919818181&source=routesms&message=00440065006D006F0020004D00650073007300610067006502100210021>

On calling the above link by replacing the username and password by your account username and password, the sms 'Demo Message!!!' should flash on the mobile no in the destination field.

The message has to be encoded in the UTF-16BE format and the type parameter has to be set to 6 i.e. (type=6).

Example Link to Submit Unicode Messages :

<http://smpp5.routesms.com:8080/bulksms/sendsms?username=XXXX&password=YYYYY&type=2&dlr=0&destination=9198121212&source=routesms&message=00440065006D006F0020004D006500730073006100670065002100210021>

On calling the above link by replacing the username and password by your account username and password, you should get the sms 'Demo Message!!!' on the mobile no in the destination field.

The message has to be encoded on the UTF-16BE format and the type parameter has to be set to 6 i.e. (type=2).

Example Link to Submit WAP Push Messages:

<http://smpp5.routesms.com:8080/bulksms/sendsms?username=XXXX&password=YYYYY&type=4&dlr=1&destination=9198181818&source=routesms&message=Test%20WAP%20Push%20Special%20Characters%3A%20%C2%B6%C2%BE%20Arabic%3A%20%D8%A6!!!&url=http%3A%2F%2Fwww.routesms.com%2F>



The following observations can be made in the above URL:-

1. 'type=4', indicates this is a WAP Push, this mode supports all characters falling under the Unicode character set both in 'message' field and 'url'.
2. 'dlr=1', indicates delivery report for this message is needed.
3. 'message=Test%20WAP%20Push%20Special%20Characters%3A%20%C2%B6%C2%BE%20Arabic%3A%20%D8%A6%20Greek%3A%20%CD%BC!!!', The message field contained the message to displayed in URL encoded format, on using the appropriate username and password in the above link you will get a service message with text, 'Test WAP Push Special Characters: ¶¾ Arabic: ﺽ Greek: ¸', on the specified cell phone, hyper linked to the web address: 'http://www.routesms.com/'
4. 'url=http%3A%2F%2Fwww.routesms.com%2F', URL Encoded format of 'http://www.routesms.com/'

Appendix

GSM 03.38 Character set

GSM 03.38																
	x0	x1	x2	x3	x4	x5	x6	x7	x8	x9	xA	xB	xC	xD	xE	xF
0x	@	£	\$	¥	è	é	ù	ì	ò	Ç	LF	Ø	ø	CR	Å	å
1x	Δ	_	Φ	Γ	Λ	Ω	Π	Ψ	Σ	Θ	Ξ	ESC	Æ	æ	ß	É
2x	SP	!	"	#	α	%	&	'	()	*	+	,	-	.	/
3x	0	1	2	3	4	5	6	7	8	9	:	;	<	=	>	?
4x	i	A	B	C	D	E	F	G	H	I	J	K	L	M	N	O
5x	P	Q	R	S	T	U	V	W	X	Y	Z	Ä	Ö	Ñ	Ü	§
6x	ı	a	b	c	d	e	f	g	h	i	j	k	l	m	n	o
7x	p	q	r	s	t	u	v	w	x	y	z	ä	ö	ñ	ü	à
1B 0x												FF				
1B 1x				^												
1B 2x								{	}							\
1B 3x													[~]	
1B 4x																
1B 5x																
1B 6x						€										
1B 7x																



ISO-8859-1 Character set

ISO/IEC 8859-1																
	x0	x1	x2	x3	x4	x5	x6	x7	x8	x9	xA	xB	xC	xD	xE	xF
0x	unused															
1x	unused															
2x	SP	!	"	#	\$	%	&	'	()	*	+	,	-	.	/
3x	0	1	2	3	4	5	6	7	8	9	:	;	<	=	>	?
4x	@	A	B	C	D	E	F	G	H	I	J	K	L	M	N	O
5x	P	Q	R	S	T	U	V	W	X	Y	Z	[\]	^	_
6x	`	a	b	c	d	e	f	g	h	i	j	k	l	m	n	o
7x	p	q	r	s	t	u	v	w	x	y	z	{		}	~	
8x	unused															
9x	unused															
Ax	NBSP	ı	¢	£	¤	¥	¦	§	¨	©	ª	«	¬	SHY	®	ˆ
Bx	°	±	²	³	´	µ	¶	·	¸	¹	º	»	¼	½	¾	¿
Cx	À	Á	Â	Ã	Ä	Å	Æ	Ç	È	É	Ê	Ë	Ì	Í	Î	Ï
Dx	Ð	Ñ	Ò	Ó	Ô	Õ	Ö	×	Ø	Ù	Ú	Û	Ü	Ý	Þ	ß
Ex	à	á	â	ã	ä	å	æ	ç	è	é	ê	ë	ì	í	î	ï
Fx	ð	ñ	ò	ó	ô	õ	ö	÷	ø	ù	ú	û	ü	ý	þ	ÿ

Code values 00-1F, 7F, and 80-9F are not assigned to characters by ISO/IEC 8859-1.